

HOT SWAPPABLE ELECTRONIC MODULE WITH NON-STAGGERED CONNECTORS

5

Inventors: Carl Meert, Victor Jochiong, Raymond Ho & Kaamel Kermaani

BACKGROUND

This invention relates to the fields of electronics and computer systems.

10 More particularly, an apparatus is provided for enabling an electronic module having non-staggered connector contacts to be installed live or hot (e.g., during operation of the system in which it is installed).

An electronic module or peripheral device that can be inserted or replaced in a system (e.g., a computer system) while the system is operating, or is live, may
15 be considered hot swappable. The use of such modules allows the system to continue operation even while a failed module is replaced, thus limiting the amount of time that the system is unavailable due to maintenance.

Typical hot swappable components include signal connectors (e.g., pins, sockets) designed to mate with compatible connectors of an interface module,
20 mid-plane assembly or system interface. The signal connectors thus provide for electrical connection between the circuitry of the component and corresponding circuitry of the system.

When the various circuits or circuit elements of a hot swappable component need to be connected or powered up in a particular sequence, the
25 component is typically configured with staggered connectors. In other words, connectors for different signal lines or circuits may be of different lengths or depths, so that when the component is mated with the system the connectors make contact in the desired sequence. In particular, a ground connector may be longer

than a power or input/output connector so that a ground reference is established before the component is energized.

The use of staggered connectors requires the hot swappable component and/or the system interface to which the component mates, to be specially
5 configured to provide or allow for connectors of varying lengths. However, some interfaces or connector assemblies that may be used with a hot swappable component may employ uniformly sized connectors. Or, staggered connectors may be unavailable, unusable or not feasible for the component.

10

SUMMARY

Thus, in one embodiment of the invention an apparatus is provided for an electronic module or component having non-staggered connectors, to ensure that the module is connected or energized in a desired sequence. The apparatus may include one or more circuit elements configured to ensure a first connection (e.g.,
15 ground) is made before a second connection (e.g., power) is completed.

In an embodiment of the invention, an electronic module that is hot swappable, or to be inserted in a system while the system is live, is configured with a switch. The switch may comprise a mechanical switch or a solid-state switch such as a FET (Field Effect Transistor). A switch gate is coupled to
20 ground and the switch therefore remains open until a ground connection is made between the module and the system. The switch is then closed and a connection between a source (e.g., power, Vcc) and the module's internal load or circuitry can be completed.

DESCRIPTION OF THE FIGURES

FIG. 1 is a block diagram depicting an electronic module, having non-staggered connectors, to be mated with a system interface in accordance with an embodiment of the present invention.

5 FIG. 2 is a block diagram demonstrating an electronic module configured for hot swapping, with non-staggered connectors, in accordance with an embodiment of the invention.

10 FIG. 3 depicts an apparatus for enabling an electronic module with non-staggered connectors to be hot swappable, in accordance with an embodiment of the present invention.

DETAILED DESCRIPTION

The following description is presented to enable any person skilled in the art to make and use the invention, and is provided in the context of particular applications of the invention and their requirements. Various modifications to the disclosed embodiments will be readily apparent to those skilled in the art and the general principles defined herein may be applied to other embodiments and applications without departing from the scope of the present invention. Thus, the present invention is not intended to be limited to the embodiments shown, but is to be accorded the widest scope consistent with the principles and features disclosed herein.

15 The program environment in which a present embodiment of the invention is executed illustratively incorporates a general-purpose computer or a special purpose device such as a hand-held computer. Details of such devices (e.g., processor, memory, data storage, display) may be omitted for the sake of clarity.

20 In one embodiment of the invention an apparatus is provided for ensuring that lines or circuits of a hot swappable electronic module with non-staggered

electrical connectors (i.e., connectors of substantially uniform length) are connected or energized in a desired sequence. The electronic module may comprise a peripheral component (e.g., storage device, input/output device), an assembly of electronic devices or circuits, an internal computer system module, and so on. The module may interface with (e.g., connect to) any portion of a computer or other system. The module is hot swappable in that it may be inserted or replaced while the system is live.

Because the module's connectors are of uniform length or depth, the desired sequence of signal/power connections is ensured through the use of a switching element within the module. Until a first connection is made (e.g., for ground), the switch remains open. When closed, a second connection (e.g., power, Vcc) is completed.

FIG. 1 illustrates an electronic module that, due to its non-staggered connectors, may subject the module or another component to damaging electrical current or erroneous signals. Illustratively, electronic module 120 is a computer system component that requires power (e.g., +12V) to drive a load (e.g., a fan, a display, a peripheral device) and which provides or exchanges information with the system through a data line.

In FIG. 1, module 120 is configured to interface with system interface 110, which may, illustratively, be a mid-plane assembly. Multiple connections are made between module 120 and interface 110; only a subset of those connections may be depicted in FIG. 1. In particular, interface 110 provides power connection 112, Vcc connection (e.g., +5V) 114, ground connection 116 and input/output connection 118.

Electronic module 120 includes power input connection 122, Vcc input connection 124, ground connection 126 and input/output connection 128. Each connection presents a connector of uniform length/depth for mating with the

corresponding connectors of system interface 110. Thus, each of power connector 122a, Vcc connector 124a, ground connector 126a and input/output connector 128a are of the same length. The connectors of module 120 may be male or female. The connectors of interface 110 and/or module 120 may be combined in a unified, blindmate or other similar unit.

Equivalent circuits 130, 132 are shown in module 120, and may represent various types and configurations of actual circuits. Input/output line 128 may be coupled to an internal circuit or may be coupled to ground 126. For example, if input/output line 128 is merely used to inform the system as to whether module 120 is connected or not (e.g., it just provides a presence indication), then the input/output line may simply be connected to ground 126 in order to drive the line to a logic low.

Because the connectors of module 120 (and system interface 110) are non-staggered, there is no physical restriction or control over which of the connections (e.g., power, Vcc, ground, input/output) is made first. As one skilled in the art will appreciate, this may cause spurious signals to be returned to the system or may cause damage to the system, system interface 110 and/or electronic module 120. For example, if the input/output connection is made first, an out of voltage signal may be propagated to the system. Or, if the power and input/output lines are connected before ground, a dangerous level of current could be returned to the system and cause damage to, or destroy, a system component.

FIG. 2 depicts an electronic module having non-staggered connectors, which is configured in accordance with an embodiment of the invention to allow it to be hot swappable and control the order in which power, signal and/or other connections are completed.

Module 220 of FIG. 2 includes power line 222, coupled to power connector 222a, for providing power to the module. Module 220 also includes

Vcc line 224 (coupled to Vcc connector 224a), ground 226 (coupled to ground connector 226a) and input/output line 228 (coupled to input/output connector 228a). The various connectors of module 220 are intended to be coupled with corresponding connectors of power line 212, Vcc line 214, ground reference 216 and input/output line 218 of system interface 210. In this embodiment, input/output line 228 provides a "present" signal to system interface 210 when the electronic module and system interface are mated, and may include appropriate elements (e.g., a rectifier) to prevent the input/output line from going lower than ground. In other embodiments, input/output line 228 may be coupled to circuitry within module 220 and may be used to carry data between the module and the system.

Connectors 222a, 224a, 226a and 228a are of uniform length or depth, and so there is no physical control over which of these connectors makes first contact with its corresponding connector of system interface 210. To ensure that the power and Vcc inputs are energized or coupled to their internal circuits, switches 230 and 232 are incorporated into module 220. Although switches are included on both power and Vcc lines in the illustrated embodiment, in other embodiments one of them may be omitted.

Gates of switches 230, 232 are coupled to ground 226, thereby keeping the switches open until ground 226 is coupled to ground reference 216.

FIG. 3 demonstrates one configuration of a switch, such as switch 230 or 232 of FIG. 2, according to one embodiment of the invention. In this embodiment, switch 300 is a solid-state switch or a FET (Field Effect Transistor).

As described above, gate 302 of switch 300 is coupled to ground, while source 304 is coupled to power (or Vcc). Drain 306 is coupled to an internal circuit of the module comprising switch 300. Resistor 310 may provide on the order of 22 kilohms of resistance.

